

FGZ75N65WE


Discrete IGBT (High-Speed W series) 650V / 75A

Features


- Low power loss
- Low switching surge and noise
- High reliability, high ruggedness (RBSOA, SCSOA etc.)

Applications

- Uninterruptible power supply
- PV Power conditioner
- Inverter welding machine



Equivalent circuit



Maximum Ratings and Characteristics

Absolute Maximum Ratings at $T_{vj}=25^{\circ}\text{C}$ (unless otherwise specified)

Items	Symbol	Characteristics	Unit	Remarks
Collector-Emitter Voltage	V_{CES}	650	V	
Gate-Emitter Voltage	V_{GES}	± 20	V	
Transient Gate-Emitter Voltage		± 30	V	$T_r < 1\mu\text{s}$
DC Collector Current	$I_{C@25}$	124	A	$T_c=25^{\circ}\text{C}$
	$I_{C@100}$	75	A	$T_c=100^{\circ}\text{C}$
Pulsed Collector Current	I_{CP}	300	A	Note *1
Turn-Off Safe Operating Area	-	300	A	$V_{CE} \leq 650\text{V}, T_{vj} \leq 175^{\circ}\text{C}$
Diode Forward Current	$I_{F@25}$	111	A	
	$I_{F@100}$	75	A	
Diode Pulsed Current	I_{FP}	300	A	Note *1
IGBT Max. Power Dissipation	P_{D_IGBT}	520	W	$T_c=25^{\circ}\text{C}$
FWD Max. Power Dissipation	P_{D_FWD}	260	W	$T_c=25^{\circ}\text{C}$
Operating Junction Temperature	T_{vj}	-40 ~ +175	$^{\circ}\text{C}$	
Storage Temperature	T_{stg}	-55 ~ +175	$^{\circ}\text{C}$	

Note *1 : Pulse width limited by T_{vjmax} .

Electrical characteristics at $T_{vj}=25^{\circ}\text{C}$ (unless otherwise specified) Static Characteristics


Description	Symbol	Conditions	min.	typ.	max.	Unit	
Zero Gate Voltage Collector Current	I_{CES}	$V_{CE} = 650\text{V}, V_{GE} = 0\text{V}$	$T_{vj}=25^{\circ}\text{C}$	-	-	250	uA
			$T_{vj}=175^{\circ}\text{C}$	-	-	2	mA
Gate-Emitter Leakage Current	I_{GES}	$V_{CE} = 0\text{V}, V_{GE} = \pm 20\text{V}$	-	-	200	nA	
Gate-Emitter Threshold Voltage	$V_{GE(th)}$	$V_{CE} = 20\text{V}, I_C = 75\text{mA}$	3.0	4.0	5.0	V	
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	$V_{GE} = 15\text{V}, I_C = 75\text{A}$	$T_{vj}=25^{\circ}\text{C}$	-	1.80	2.20	V
			$T_{vj}=125^{\circ}\text{C}$	-	2.05	-	
			$T_{vj}=175^{\circ}\text{C}$	-	2.10	-	
Input Capacitance	C_{ies}	$V_{CE}=25\text{V}$	-	5300	-	pF	
Output Capacitance	C_{oes}	$V_{GE}=0\text{V}$	-	150	-		
Reverse Transfer Capacitance	C_{res}	$f=1\text{MHz}$	-	120	-		
Gate Charge	Q_G	$V_{CC} = 520\text{V}$ $I_C = 75\text{A}$ $V_{GE} = 15\text{V}$	-	300	-	nC	
Turn-On Delay Time	$t_{d(on)}$	$T_{vj} = 25^{\circ}\text{C}, V_{CC} = 400\text{V}$ $I_C = 37.5\text{A}, V_{GE} = 15\text{V}$ $R_G = 10\Omega$	-	34	-	ns	
Rise Time	t_r		-	25	-		
Turn-Off Delay Time	$t_{d(off)}$		-	300	-		
Fall Time	t_f	Energy loss include "tail" and FWD reverse recovery.	-	32	-	mJ	
Turn-On Energy	E_{on}		-	0.37	-		
Turn-Off Energy	E_{off}		-	0.68	-		
Turn-On Delay Time	$t_{d(on)}$	$T_{vj} = 150^{\circ}\text{C}, V_{CC} = 400\text{V}$ $I_C = 37.5\text{A}, V_{GE} = 15\text{V}$ $R_G = 10\Omega$	-	31	-	ns	
Rise Time	t_r		-	26	-		
Turn-Off Delay Time	$t_{d(off)}$		-	360	-		
Fall Time	t_f	Energy loss include "tail" and FWD reverse recovery.	-	15	-	mJ	
Turn-On Energy	E_{on}		-	0.78	-		
Turn-Off Energy	E_{off}		-	0.86	-		
Forward Voltage Drop	V_F	$I_F=75\text{A}$	$T_{vj}=25^{\circ}\text{C}$	-	2.5	3.2	V
			$T_{vj}=125^{\circ}\text{C}$	-	1.9	-	V
			$T_{vj}=175^{\circ}\text{C}$	-	1.7	-	V
Diode Reverse Recovery Time	t_{rr}	$V_{CC}=400\text{V}, I_F = 37.5\text{A}$	-	180	-	ns	
Diode Reverse Recovery Charge	Q_{rr}	$-di_F/dt=300\text{A}/\mu\text{s}, T_{vj}=25^{\circ}\text{C}$	-	0.41	-	μC	
Diode Reverse Recovery Time	t_{rr}	$V_{CC}=400\text{V}, I_F=37.5\text{A}$	-	190	-	ns	
Diode Reverse Recovery Charge	Q_{rr}	$-di_F/dt=300\text{A}/\mu\text{s}, T_{vj}=150^{\circ}\text{C}$	-	1.50	-	μC	

● Thermal Resistance


Description	Symbol	min.	typ.	max.	Unit
Thermal Resistance, Junction-Ambient	$R_{th(j-a)}$	-	-	50	°C/W
Thermal Resistance, IGBT Junction to Case	$R_{th(j-c)}_{IGBT}$	-	-	0.286	°C/W
Thermal Resistance, FWD Junction to Case	$R_{th(j-c)}_{FWD}$	-	-	0.568	°C/W

■ Characteristics (Representative)


Graph.1
DC Collector Current vs T_c
 $V_{GE} \geq +15V, T_{vj} \leq 175^\circ C$




Graph.2
FBSOA
Duty=0(Single pulse), $T_c=25^\circ C$




Graph.3
Typical Output Characteristics ($V_{CE}-I_c$)
 $T_{vj}=25^\circ C$




Graph.4
Typical Output Characteristics ($V_{CE}-I_c$)
 $T_{vj}=175^\circ C$




Graph.5
Typical Transfer Characteristics
 $V_{CE}=10V$




Graph.6
Gate Threshold Voltage vs. T_{vj}
 $I_c=75mA, V_{CE}=20V$




Graph.7
Typical Capacitance
 $V_{GE}=0V, f=1MHz, T_{vj}=25^{\circ}C$




Graph.8
Typical Gate Charge
 $V_{CC}=520V, I_c=75A, T_{vj}=25^{\circ}C$




Graph.9
Typical switching time vs. I_c
 $T_{vj}=150^{\circ}C, V_{CC}=400V$
 $V_{GE}=15V, R_G=10\Omega$




Graph.10
Typical switching time vs. R_G
 $T_{vj}=150^{\circ}C, V_{CC}=400V, I_c=37.5A$
 $V_{GE}=15V$




Graph.11
Typical switching losses vs. I_c
 $T_{vj}=150^{\circ}C, V_{CC}=400V$
 $V_{GE}=15V, R_G=10\Omega$




Graph.12
Typical switching losses vs. R_G
 $T_{vj}=150^{\circ}C, V_{CC}=400V, I_c=37.5A$
 $V_{GE}=15V$




Graph.13
FWD Forward voltage drop (V_F - I_F)




Graph.14
Typical reverse recovery characteristics vs. I_F
 $T_{vj}=150^\circ\text{C}$, $V_{CC}=400\text{V}$, $L=500\mu\text{H}$
 $V_{GE}=15\text{V}$, $R_G=10\Omega$




Graph.15
Typical reverse recovery loss vs. I_F
 $T_{vj}=150^\circ\text{C}$, $V_{CC}=400\text{V}$, $L=500\mu\text{H}$
 $V_{GE}=15\text{V}$, $R_G=10\Omega$




Graph.16
Reverse biased Safe Operating Area
 $T_{vj} \leq 175^\circ\text{C}$, $V_{GE}=+15\text{V}/0\text{V}$, $R_G=10\Omega$



Graph.17
Transient thermal resistance of IGBT





Graph.18
Transient thermal resistance of FWD




■ Outline Drawings, mm

Outview : TO-247-4L Package



DIMENSIONS ARE IN MILLIMETERS.

CONNECTION



WARNING

1. This Catalog contains the product specifications, characteristics, data, materials, and structures as of March 2017. The contents are subject to change without notice for specification changes or other reasons. When using a product listed in this Catalog, be sur to obtain the latest specifications.
2. All applications described in this Catalog exemplify the use of Fuji's products for your reference only. No right or license, either express or implied, under any patent, copyright, trade secret or other intellectual property right owned by Fuji Electric Co., Ltd. is (or shall be deemed) granted. Fuji Electric Co., Ltd. makes no representation or warranty, whether express or implied, relating to the infringement or alleged infringement of other's intellectual property rights which may arise from the use of the applications described herein.
3. Although Fuji Electric Co., Ltd. is enhancing product quality and reliability, a small percentage of semiconductor products may become faulty. When using Fuji Electric semiconductor products in your equipment, you are requested to take adequate safety measures to prevent the equipment from causing a physical injury, fire, or other problem if any of the products become faulty. It is recommended to make your design failsafe, flame retardant, and free of malfunction.
4. The products introduced in this Catalog are intended for use in the following electronic and electrical equipment which has normal reliability requirements.
 - Computers
 - OA equipment
 - Communications equipment (terminal devices)
 - Measurement equipment
 - Machine tools
 - Audiovisual equipment
 - Electrical home appliances
 - Personal equipment
 - Industrial robots etc.
5. If you need to use a product in this Catalog for equipment requiring higher reliability than normal, such as for the equipment listed below, it is imperative to contact Fuji Electric Co., Ltd. to obtain prior approval. When using these products for such equipment, take adequate measures such as a backup system to prevent the equipment from malfunctioning even if a Fuji's product incorporated in the equipment becomes faulty.
 - Transportation equipment (mounted on cars and ships)
 - Trunk communications equipment
 - Traffic-signal control equipment
 - Gas leakage detectors with an auto-shut-off feature
 - Emergency equipment for responding to disasters and anti-burglary devices
 - Safety devices
 - Medical equipment
6. Do not use products in this Catalog for the equipment requiring strict reliability such as the following and equivalents to strategic equipment (without limitation).
 - Space equipment
 - Aeronautic equipment
 - Nuclear control equipment
 - Submarine repeater equipment
7. Copyright ©1996-2017 by Fuji Electric Co., Ltd. All rights reserved.
No part of this Catalog may be reproduced in any form or by any means without the express permission of Fuji Electric Co., Ltd.
8. If you have any question about any portion in this Catalog, ask Fuji Electric Co., Ltd. or its sales agents before using the product. Neither Fuji Electric Co., Ltd. nor its agents shall be liable for any injury caused by any use of the products not in accordance with instructions set forth herein.