

Replacement for BU series (ESB/FSB/FHB) - 240VAC application

Revised May 2009
Fuji Electric Corp of America, D&C Dep.

		BU series (Discontinue product)						G-TWIN series						BU-C series					
Frame size (A)	Poles	Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)		
			240V		W	H	D		240V		W	H	D		240V		W	H	D
100	2	BU-ESB2	22	15,20,25,30,35,40,45,50,60	105	168	86	BW125JAGU-2P (BW125RAGU-2P)	50 (100)	15,20,30,40,50,60	60 (90)	171 (171)	68	BU2EHC	18	15,20,25,30,35,40,45,50,60	70	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
	3	BU-ESB3	22	15,20,25,30,35,40,45,50,60	105	168	86	BW125JAGU-3P	50	15,20,30,40,50,60	90	171	68	BU3EHC	18	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FSB2	30	15,20,25,30,35,40,45,50,60	105	168	86	BW125JAGU-2P (BW125RAGU-2P)	50 (100)	15,20,30,40,50,60	60 (90)	171 (171)	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100, 125						100			
				125,150						125,150,160,175,200 225,250									
	3	BU-FSB3	30	15,20,25,30,35,40,45,50,60	105	168	86	BW125JAGU-3P	50	15,20,30,40,50,60	90	155	60	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
				125,150						125,150,160,175,200 225,250						125,150			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
				125,150						125,150,160,175,200,225,250									
	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
				125,150						125,150,160,175,200,225,250									
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FHB2	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	100	15,20,30,40,50,60	90	171	68	BU2FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	3	BU-FHB3	65	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	100	15,20,30,40,50,60	90	171	68	BU3FHC	65	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			

		BU series (Discontinue product)						G-TWIN series						BU-C series						
Frame size (A)	Poles	Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			
			480V		W	H	D				W	H	D				480V	W	H	D
100	2	BU-ESB2	14	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	50	15,20,30,40,50,60	90	171	68	BU2EHC	14	15,20,25,30,35,40,45,50,60	70	160	86	
				70						70,75						70				
				80,90						80,90						80,90				
				100						100,125						100				
	3	BU-ESB3	14	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	50	15,20,30,40,50,60	90	171	68	BU3EHC	14	15,20,25,30,35,40,45,50,60	105	160	86	
				70						70,75						70				
				80,90						80,90						80,90				
				100						100,125						100				
	150	2	BU-FSB2	22	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	50	15,20,30,40,50,60	90	171	68	BU2FHC	25	15,20,25,30,35,40,45,50,60	105	160	86
					70						70,75						70			
80,90					80,90						80,90									
100					100,125						100									
125,150																				
3		BU-FSB3	22	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	50	15,20,30,40,50,60	90	171	68	BU3FHC	25	15,20,25,30,35,40,45,50,60	105	160	86	
				70						70,75						70				
				80,90						80,90						80,90				
				100						100,125						100				
				125,150																
150	2	BU-FHB2	25	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	50	15,20,30,40,50,60	90	171	68	BU2FHC	25	15,20,25,30,35,40,45,50,60	105	160	86	
				70						70,75						70				
				80,90						80,90						80,90				
				100						100,125						100				
				125,150																
	3	BU-FHB3	25	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	50	15,20,30,40,50,60	90	171	68	BU3FHC	25	15,20,25,30,35,40,45,50,60	105	160	86	
				70						70,75						70				
				80,90						80,90						80,90				
				100						100,125						100				
				125,150																

Replacement for BU series (ESB/FSB/FHB) - 600Y/347VAC application

Revised May 2009
Fuji Electric Corp of America, D&C Dep.

		BU series (Discontinue product)						G-TWIN series						BU-C series					
Frame size (A)	Poles	Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)		
			600V		W	H	D		600Y/347V		W	H	D		600V		W	H	D
100	2	BU-ESB2	14	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	18	15,20,30,40,50,60	90	171	68	BU2EHC	14	15,20,25,30,35,40,45,50,60	70	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
	3	BU-ESB3	14	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	18	15,20,30,40,50,60	90	171	68	BU3EHC	14	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
150	2	BU-FSB2	14	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	18	15,20,30,40,50,60	90	171	68	BU2FHC	18	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
				125,150				BW250RAGU-2P	25	125,150,160,175,200	105	181	68	BU-JSB2	22	125,150,175,200,225	140	257	103
										225,250						250			
	3	BU-FSB3	14	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	18	15,20,30,40,50,60	90	171	68	BU3FHC	18	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
				125,150				BW250RAGU-3P	25	125,150,160,175,200	105	181	68			125,150			
										225,250									
150	2	BU-FHB2	18	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	18	15,20,30,40,50,60	90	171	68	BU2FHC	18	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
				125,150				BW250RAGU-2P	25	125,150,160,175,200	105	181	68	BU-JSB2	22	125,150,175,200,225	140	257	103
										225,250						250			
	3	BU-FHB3	18	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-3P	18	15,20,30,40,50,60	90	171	68	BU3FHC	18	15,20,25,30,35,40,45,50,60	105	160	86
				70						70,75						70			
				80,90						80,90						80,90			
				100						100,125						100			
				125,150				BW250RAGU-3P	25	125,150,160,175,200	105	181	68			125,150			
										225,250									

Replacement for BU series (ESB/FSB/FHB) - 600VAC application

Revised May 2009
Fuji Electric Corp of America, D&C Dep.

		BU series (Discontinue product)						G-TWIN series						BU-C series						
Frame size (A)	Poles	Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)	Rated Current (A)	Dimensions (mm)			
			600V		W	H	D		600V		W	H	D		600V		W	H	D	
100	2	BU-ESB2	14	15,20,25,30,35,40,45,50,60	105	168	86						BU2EHC	14	15,20,25,30,35,40,45,50,60			70	160	86
				70											70					
				80,90											80,90					
				100											100					
	3	BU-ESB3	14	15,20,25,30,35,40,45,50,60	105	168	86						BU3EHC	14	15,20,25,30,35,40,45,50,60			105	160	86
				70											70					
				80,90											80,90					
				100											100					
150	2	BU-FSB2	14	15,20,25,30,35,40,45,50,60	105	168	86						BU2FHC	18	15,20,25,30,35,40,45,50,60			105	160	86
				70											70					
				80,90											80,90					
				100											100					
				125,150																
	3	BU-FSB3	14	15,20,25,30,35,40,45,50,60	105	168	86						BU3FHC	18	15,20,25,30,35,40,45,50,60			105	160	86
				70											70					
				80,90											80,90					
				100											100					
				125,150											125,150					
150	2	BU-FHB2	18	15,20,25,30,35,40,45,50,60	105	168	86						BU2FHC	18	15,20,25,30,35,40,45,50,60			105	160	86
				70											70					
				80,90											80,90					
				100											100					
				125,150																
	3	BU-FHB3	18	15,20,25,30,35,40,45,50,60	105	168	86						BU3FHC	18	15,20,25,30,35,40,45,50,60			105	160	86
				70											70					
				80,90											80,90					
				100											100					
				125150											125,150					

Replacement for BU series (FHB) - 125/250VDC application

Revised July 2008
Fuji Electric Corp of America, D&C Dep.

BU series (Discontinue product)									G-TWIN series							BU-C series						
Frame size (A)	Poles	Type	Rated I.C (kA)		Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)		Rated Current (A)	Dimensions (mm)			Type	Rated I.C (kA)		Rated Current (A)	Dimensions (mm)		
			DC125/250V	DC250V		W	H	D		DC125/250V	DC250V		W	H	D		DC125/250V	DC250V		W	H	D
150	2	BU-FHB2	10	-	15,20,25,30,35,40,45,50,60	105	168	86	BW125RAGU-2P	10	-	15,20,30,40,50,60	90	171	68	BU2FHC	20	-	15,20,25,30,35,40,45,50,60	105	165.5	86
					70							70,75							70			
					80,90							80,90							80,90			
					100							100,125							100			
					125,150				BW250JAGU-2P	10	-	125,150,160,175,200,225,250	105	181	68	BU-JHB2	10	10	125,150	140	257	103

Replacement for BU series(ESB/FSB/FHB) -Accessories-

Revised May 2009, FECOA D&C Dep.

1 / 2

Accessories name	G-TWIN / BU-C series		BU series (Discontinued)		Exchangeable	
	Breaker type	Accessories part#	Breaker type	Accessories part#	BU accessories SA-UL/BU-C	BU accessories SA-UL/BU-C
Operating Handle	N	BW125JAGU-2P	Not available	BU-ESB2	N-13A-Q-00905	No
		BW125JAGU-3P	BW9N0CA	BU-ESB3		
		BW125RAGU-2P				
		BW125RAGU-3P				
		BU2EHC	BZ0NFH			
		BU3EHC				
		BU2FHC	BZ0NFH	BU-FSB2		
		BU3FHC		BU-FSB3		
		BW250JAGU-2P	BW9N0GA	BU-FHB2		
		BW250JAGU-3P		BU-FHB3		
Operating Handle	V	BW125JAGU-2P	Not available	BU-ESB2	—	No
		BW125JAGU-3P	BW9V0CA	BU-ESB3		
		BW125RAGU-2P				
		BW125RAGU-3P				
		BU2EHC	BZ0VFH			
		BU3EHC				
		BU2FHC	BZ0VFH	BU-FSB2		
		BU3FHC		BU-FSB3		
		BW250JAGU-2P	BW9V0GA	BU-FHB2		
		BW250JAGU-3P		BU-FHB3		
Operating Handle	G	BW125JAGU-2P	Not available	BU-ESB2	BU-GGD	No
		BW125JAGU-3P		BU-ESB3		
		BW125RAGU-2P				
		BW125RAGU-3P				
		BU2EHC	Not available			
		BU3EHC				
		BU2FHC	Not available	BU-FSB2		
		BU3FHC		BU-FSB3		
		BW250JAGU-2P	Not available	BU-FHB2		
		BW250JAGU-3P		BU-FHB3		
Terminal Cover		BW125JAGU-2P	Short type	BU-ESB2	BU-CFHA	No
		BW125JAGU-3P	(Gray-white)	BU-ESB3		No
		BW125RAGU-2P	* provided with breaker			
		BW125RAGU-3P				
		BW125JAGU-2P	Long tyoe			
		BW125JAGU-3P	(Gray-white)			
		BW125RAGU-2P				
		BW125RAGU-3P				
		BU2EHC	BZ-CFHB-2			
		BU3EHC	BZ-CFHB-3			
		BU2FHC	BZ-CFHB-3	BU-FSB2	BU-CFHA	No
		BU3FHC		BU-FSB3		No
		BW250JAGU-2P	Short type	BU-FHB2	BU-CFHA	No
		BW250JAGU-3P	(Gray-white)	BU-FHB3		No
		BW250RAGU-2P	* provided with breaker			
		BW250RAGU-3P				
		BW250JAGU-2P	Long type			
		BW250JAGU-3P	(Gray-white)			
		BW250RAGU-2P				
		BW250RAGU-3P				

Replacement for BU series(ESB/FSB/FHB) -Accessories-

Revised May 2009, FECOA D&C Dep.

2 / 2

Accessories name	G-TWIN / BU-C series		BU series (Discontinued)		Exchangeable	
	Breaker type	Accessories part#	Breaker type	Accessories part#	BU accessories SA-UL/BU-C accessories BU	
Insulation Barrier	BW125JAGU-2P	BW9BPCA	BU-ESB2	B-13A	No	No
	BW125JAGU-3P	* provided with breaker	BU-ESB3			
	BW125RAGU-2P					
	BW125RAGU-3P					
	BU2EHC	Not available				
	BU3EHC					
	BU2FHC	Not available	BU-FSB2	B-13A	No	No
	BU3FHC		BU-FSB3			
	BW250JAGU-2P	BW9BPGA	BU-FHB2	B-13A	No	No
	BW250JAGU-3P	* provided with breaker	BU-FHB3			
Lug Terminal Kit	BW125JAGU-2P	BW9WSL0CA-3 GLOBAL	BU-ESB2	BU-TA100	No	No
	BW125JAGU-3P		BU-ESB3			
	BW125RAGU-2P					
	BW125RAGU-3P					
	BU2EHC	To be advised				
	BU3EHC					
	BU2FHC	To be advised	BU-FSB2	BU-TA100	No	No
	BU3FHC		BU-FSB3			
	BW250JAGU-2P	BW9WSL0GA-3 GLOBAL (125-175A)	BU-FHB2	BU-TA100	No	No
	BW250JAGU-3P	BW9WSL1GA-3 GLOBAL (200-250A)	BU-FHB3			
Flat Terminal	BW125JAGU-2P	BW9S0CA-3 GLOBAL	BU-ESB2	LINE:BU-S152R LOAD:BU-S152U	No	No
	BW125JAGU-3P					
	BW125RAGU-2P		BU-ESB3	LINE:BU-S153R LOAD:BU-S153U	No	No
	BW125RAGU-3P					
	BU2EHC	BU-S102B				
	BU3EHC	BU-S103B				
	BU2FHC	BU-S102B	BU-FSB2	LINE:BU-S152R LOAD:BU-S152U	No	No
	BU3FHC	BU-S103B				
	BW250JAGU-2P	BZ-S50B-2253 GLOBAL	BU-FSB3	LINE:BU-S153R LOAD:BU-S153U	No	No
	BW250JAGU-3P					
Handle locking key	BW125JAGU-2P	BW9Q1CA	BU-ESB2	BU-ESB_Q1	No	No
	BW125JAGU-3P		BU-ESB3			
	BW125RAGU-2P					
	BW125RAGU-3P					
	BU2EHC	Not available				
	BU3EHC					
	BU2FHC	Not available	BU-FSB2	BU-FSB_Q1	No	No
	BU3FHC		BU-FSB3			
	BW250JAGU-2P	BW9Q1CA	BU-FHB2	BU-FHB_Q1	No	No
	BW250JAGU-3P		BU-FHB3			
Handle locking key	BW125JAGU-2P	BW9Q2CA	BU-ESB2	BU-ESB_Q2	No	No
	BW125JAGU-3P		BU-ESB3			
	BW125RAGU-2P					
	BW125RAGU-3P					
	BU2EHC	Not available				
	BU3EHC					
	BU2FHC	Not available	BU-FSB2	BU-FSB_Q2	No	No
	BU3FHC		BU-FSB3			
	BW250JAGU-2P	BW9Q2GA	BU-FHB2	BU-FHB_Q2	No	No
	BW250JAGU-3P		BU-FHB3			
	BW250RAGU-2P					
	BW250RAGU-3P					