

Inlet Filters & Covers

Designed to protect and filter air.




Fuji Electric Inlet Filters are designed to protect Ring Compressors by filtering the inlet air when used for pressure applications. The filter has a perforated outer cylinder and an inner liner wrapped with a fine mesh (.009) screen. The filter itself is rated for 200-micron filtration.

Fuji Electric Filter Covers designed to fit over the Inlet Filter and provide additional air filtration and protection. They are made from 100% polyester fiber filter media, approximately 3/4" thick, with high dirt holding capacity while preventing surface loading.

- Most economical, simple, and efficient protection for your ring compressor/blower.
- Cast aluminum end covers with zinc-plated hardware and perforated guards.
- Each Filter comes with the one Cover.
- Filter Cover is easily re-ordered and replaced and may even be cleaned and re-used.
- Filter Cover keeps filter cleaner for long lasting performance and minimum maintenance.

Technical Specifications

- Inlet Filter operates at less than 1% pressure loss when properly sized for ring compressor.
- Polyester Filter Cover is flame-retardant with a bonded tacky side for maximum dirt holding capacity. Can be used at temperature of 300°F. Rated at 83% efficient at 25 microns with minimal pressure loss.
- Not Recommended for outdoor applications, Filter must be protected from the elements.



| Model # | Use with Blower Model: | Dim. A (in.) | Dim. B (in.) | Dim. C (in.) | Connection Type | Micron Rating* | Replacement Cover | Weight (lbs.) |
|---------|---------------------------------|-----------------|-----------------|-----------------|--------------------|-------------------|----------------------|------------------|
| F-123 | VFC080-VFC300 | 8 | 4 | 1 - 1/4 | (F)NPT | 25 | C-123 | 3.5 |
| F-45 | VFC400-VFC508; VFZ401-VFZ501 | 8 | 5 - 1/4 | 1 - 1/2 | (F)NPT | 25 | C-45 | 8 |
| F-67 | VFZ601-VFZ701 | 12 - 1/2 | 5 - 1/4 | 2 | (F)NPT | 25 | C-67 | 14 |
| F-89 | VFZ801-VFZ901 | 23 | 6 - 7/8 | 3 | MPT | 25 | C-89 | 29 |

*With Cover.